



ART 67-01

A.R.T. P524

Mod. « P 524 »

GAMME D'ONDA

Onde corte 18 ÷ 52 m.

Onde medie 190 ÷ 580 m.

Presa fono - Uscita: 3 W.

VALVOLE

V₁ = 6A8-G

V₂ = 6K7-G

R₂ = 50.000 Ω 1/2 W

R₃ = 50.000 Ω 1 W

R₄ = 20.000 Ω 1 W

R₅ = 300 Ω 1/2 W

R₆ = 50.000 Ω 1 W

R₇ = 50.000 Ω 1/2 W

R₈ = 4000 Ω 1/2 W

R₉ = 0,5 MΩ 1/2 W

R₁₀ = 1 MΩ Potenziometro in interruttore

C_{1A} = 25 pF mica

C₁ = 0,1 μF 1500 V

C₂ = 0,1 μF 1500 V

C₃ = 250 pF mica

C₄ = 125 pF mica

C₅ = 0,1 μF 1000 V

C₆ = 0,1 μF 1000 V

C₇ = 0,1 μF 1500 V

C₈ = 0,1 μF 1500 V

C₉ = 250 pF mica

C₁₀ = 100 pF mica